

ATEO6 Wall speaker with CleverMount™ 6"

Highlights:

- Vertical and horizontal mounting (rotatable logo)
- 1" Dome tweeter
- 6" Low frequency loudspeaker
- 100V and low impedance connection possibility
- Stunning designed and elegant looking ABS enclosure
- Patented CleverMount™ mounting system
- · Multi-tapping 70V / 100V line transformer

Product information:

The ATEO is a series of extraordinary loudspeakers especially designed for fixed install indoor applications, ranging from modern residential applications to the most demanding designer applications in environments such as retail stores, pubs, restaurants or even clubs.

The ATEO6 is the 6" version, with a 1" dome tweeter and a 6" Mid / Low frequency driver, ensuring a true-to-nature, high-fidelity reproduction of music and speech. It features a stunningly designed and elegant looking ABS housing which is fitted with high-quality components. What makes this loudspeaker range so exceptional is the especially designed mounting bracket using the Clevermount™ technology, making the loudspeakers cabinet flow together with the mounting bracket providing a great ease for installing the loudspeaker in one good-looking entity.

The mounting and connection of the loudspeaker simply happens by attaching the included metal wall-plate to the desired location. When mounted, the wires must be connected to the desired terminal of the custom connection block. The desired power tap for 70/100 Volt or 8 Ohm can be selected by picking the right terminal. After this is done, only five seconds of work is left for clipping the loudspeaker onto the wall-plate, tightening the safety screw and you're ready to rock! This way, it's really child's play to install a large number of loudspeakers in no-time

Even if you're working all alone while people are watching your fingers or when installing the speakers up high, when you're standing on a ladder. All ATEO series speakers are available in black (/B) or white (/W).

Applications:

- · Bars & Restaurants
- Corporate
- Education
- Hotels
- Retail
- · Residential
- Clubs







Impedance:

 Ω 80hm Ω 160hm

Voltage:

70-100 Volt

System specifications:

Peak power handling 240 W Program power handling 120 W RMS/AES power handling 60 W Impedance 8 Ω (ATEO6) Incline angle Left 30° Incline angle Left 30° Right 30° 30° Sensitivity (1W/1m) 89 dB 80 Sound Pressure (Max. W/1m) @ 8 Ω 106 dB @ 100 V 105 dB Frequency Response (± 3 dB) 65 Hz - 20 kHz Dispersion Horizontal 120° Connectors Vertical 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter 6"MF / LF Woofer 6"MF / LF Woofer Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W	Speaker type		Full range
$\begin{tabular}{ c c c c c c c } \hline RMS/AES power handling \\ Impedance & 8 Ω (ATEO6) \\ \hline Incline angle & Left & 30° \\ \hline Right & 30° \\ \hline Right & 30° \\ \hline Bottom & 30° \\ \hline Top & 5° \\ \hline Sensitivity (1W/1m) & 89 dB \\ \hline Sound Pressure (Max. W/1m) & $\emptyset $8 Ω & 106 dB \\ \hline \emptyset 100 V & 105 dB \\ \hline Frequency & Response (\pm 3 \ dB)$ & 65 Hz - 20 \ kHz$ \\ \hline Range (-10 \ dB) & 55 Hz - 20 \ kHz$ \\ \hline Dispersion & Horizontal & 120° \\ \hline Connectors & θ-pin Custom Terminal Block \\ \hline Drivers & $1"$ Dome tweeter \\ \hline Environment Tappings & 1 & 100 $\Omega - 100 $V / Not used - 70 $V / 50 W \\ \hline \end{tabular}$	Peak power handling		240 W
Impedance 8 Ω (ATEO6) Incline angle Left 30° Right 30° Bottom 30° Sensitivity (1W/1m) 89 dB Sound Pressure (Max. W/1m) @ 8 Ω 106 dB © 100 V 105 dB Frequency Response (± 3 dB) 65 Hz - 20 kHz Dispersion Horizontal 120° Connectors Vertical 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter Eline Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W	Program power handling		120 W
Incline angle Left 30° Right 30° Bottom 30° Top 5° Sensitivity (1W/1m) 89 dB Sound Pressure (Max. W/1m) @ 8 Ω 106 dB © 100 V 105 dB Frequency Response (± 3 dB) 65 Hz - 20 kHz Dispersion Horizontal 120° Vertical 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W	RMS/AES power handling		60 W
Incline angle Left 30° Right 30° Bottom 30° Top 5° Sensitivity (1W/1m) 89 dB Sound Pressure (Max. W/1m) @ 8 Ω 106 dB © 100 V 105 dB Frequency Response (± 3 dB) 65 Hz - 20 kHz Range (-10 dB) 55 Hz - 20 kHz Dispersion Horizontal 120° Connectors Vertical 120° Connectors 1" Dome tweeter 6° MF / LF Woofer Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W	Impedance		8 Ω (ATEO6)
Right 30° Bottom 30° Top 5° Sensitivity (1W/1m) 89 dB Sound Pressure (Max. W/1m) @ 8 Ω 106 dB @ 100 V 105 dB Frequency Response (± 3 dB) 65 Hz - 20 kHz Range (-10 dB) 55 Hz - 20 kHz Dispersion Horizontal 120° Connectors Vertical 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter 6" MF / LF Woofer Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W			16 Ω (ATEO6D)
Bottom 30° Top 5° Sensitivity (1W/1m) 89 dB Sound Pressure (Max. W/1m) @ 8 Ω 106 dB Frequency Response (± 3 dB) 65 Hz - 20 kHz Prequency Range (-10 dB) 55 Hz - 20 kHz Dispersion Horizontal 120° Connectors Vertical 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter 6" MF / LF Woofer Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W	Incline angle	Left	30°
Top 5° Sensitivity (1W/1m) 89 dB Sound Pressure (Max. W/1m) @ 8 Ω 106 dB © 100 V 105 dB Frequency Response (± 3 dB) 65 Hz - 20 kHz Range (-10 dB) 55 Hz - 20 kHz Dispersion Horizontal 120° Vertical 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter 6" MF / LF Woofer Line Transformer Tappings 1		Right	30°
Sensitivity (1W/1m) 89 dB Sound Pressure (Max. W/1m) @ 8 Ω 106 dB © 100 V 105 dB Frequency Response (± 3 dB) 65 Hz - 20 kHz Range (-10 dB) 55 Hz - 20 kHz Dispersion Horizontal 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W		Bottom	30°
Sound Pressure (Max. W/1m) @ 8 Ω 106 dB @ 100 V 105 dB Frequency Response (± 3 dB) 65 Hz - 20 kHz Range (-10 dB) 55 Hz - 20 kHz Dispersion Horizontal 120° Connectors Vertical 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter Eine Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W		Тор	5°
© 100 V 105 dB Frequency Response (± 3 dB) 65 Hz - 20 kHz Range (-10 dB) 55 Hz - 20 kHz Dispersion Horizontal 120° Vertical 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter 6" MF / LF Woofer Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W	Sensitivity (1W/1m)		89 dB
Frequency Response (± 3 dB) 65 Hz - 20 kHz Range (-10 dB) 55 Hz - 20 kHz Dispersion Horizontal 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter Eine Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W	Sound Pressure (Max. W/1m)	@ 8 Ω	106 dB
Range (-10 dB)55 Hz - 20 kHzDispersionHorizontal120°Vertical120°Connectors6-pin Custom Terminal BlockDrivers1" Dome tweeterLine Transformer Tappings1100 Ω - 100 V / Not used - 70 V / 50 W		@ 100 V	105 dB
Dispersion Horizontal 120° Vertical 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter 6" MF / LF Woofer Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W	Frequency	Response (± 3 dB)	65 Hz - 20 kHz
Vertical 120° Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter 6" MF / LF Woofer Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W		Range (-10 dB)	55 Hz - 20 kHz
Connectors 6-pin Custom Terminal Block Drivers 1" Dome tweeter 6" MF / LF Woofer Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W	Dispersion	Horizontal	120°
Drivers 1" Dome tweeter 6" MF / LF Woofer Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W		Vertical	120°
Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W	Connectors		6-pin Custom Terminal Block
Line Transformer Tappings 1 100 Ω - 100 V / Not used - 70 V / 50 W	Drivers		1" Dome tweeter
			6" MF / LF Woofer
2 200 Ω - 100 V / 50 W - 70 V / 25 W	Line Transformer Tappings	1	100 Ω - 100 V / Not used - 70 V / 50 W
		2	200 Ω - 100 V / 50 W - 70 V / 25 W
3 400 Ω - 100 V / 25 W - 70 V / 12.5 W		3	400 Ω - 100 V / 25 W - 70 V / 12.5 W
4 800 Ω - 100 V / 12.5 W - 70 V / 6.25 W		4	800 Ω - 100 V / 12.5 W - 70 V / 6.25 W

Product Features:

Dimensions		193.1 x 347.5 x 215.2 mm (W x H x D)
Weight		3.820 kg
Operating temperature		-20 °C ~ 60 °C
Mounting		Clevermount™
Accessories	Included	Allen-key wrench
Construction		ABS
Front finish		Steel grill
Colours		Black (RAL9005) (ATEO6/B, ATEO6D/B)
		White (RAL9003) (ATEO6/W, ATEO6D/W)

Variants:

- ATEO6/W White version 8Ω and 100V
- ATEO6D/B Black version 16Ω
- ATEO6D/W White version 16Q

Shipping & Ordering:

Packaging	Cardboard box (pair)
Shipping weight & volume	8.200 kg - 0.038 Cbm (2 pcs)

Architects' and Engineers' Specifications:

The loudspeaker shall be a 2-way system, consisting of a 6″ woofer and 1″ dome tweeter which are housed in a curved ABS housing with a fine perforated steel front grill. The connection and installation of the loudspeaker shall be performed using a Clevermount™ mounting system. The direction of the speaker shall be continuously adjustable in all four directions. It shall have an RMS power handling of 60 Watt with a maximum power handling of 120 Watt and the frequency response (±3 dB) shall range from 65 Hz to 20 kHz. The sensitivity shall be 89 dB when measuring with an input signal of 1 Watt at a distance of 1 meter, while the maximum continuous sound pressure level shall be 106 dB. The loudspeaker shall have an impedance of 8 Ohm and contain a passive built-in crossover network. For use in public address systems, a Multi-Tapping 100 Volt built-in line transformer with power taps for 50 Watt, 25 Watt, 12.5 Watt and 6.25 Watt shall be provided. The corresponding power tap shall be selectable by connecting the correct terminal of a special designed 6-pin terminal block connector. The system's enclosure shall be 347,1 mm high, 193,1 mm wide and 215,2 mm deep and the weight shall not exceed 3.82 Kg.

Horizontal Polars:



